

## PAR9X12BH-IP DMX Chart

### 6-Channel Mode

Channel	Value	Function	Description
1	0-255	Red Intensity	Red 0-100%
2	0-255	Green Intensity	Green 0-100%
3	0-255	Blue Intensity	Blue 0-100%
4	0-255	White Intensity	White 0-100%
5	0-255	Amber Intensity	Amber 0-100%
6	0-255	UV Intensity	UV 0-100%

### 10-Channel Mode

Channel	Value	Function	Description
1	0-255	Master Dimmer	All colours 0-100%
2	0-255	Red Intensity	Red 0-100%
3	0-255	Green Intensity	Green 0-100%
4	0-255	Blue Intensity	Blue 0-100%
5	0-255	White Intensity	White 0-100%
6	0-255	Amber Intensity	Amber 0-100%
7	0-255	UV Intensity	UV 0-100%
8	0-9	Strobe	Strobe off
	10-255		Strobe speed adjustment
9	0-9	No function	
	10-50	Auto Jump	
	51-100	Auto Fade	
	101-150	Auto Pulse	
	151-200	Auto Combined	
	201-255	No function	
10	1-255	Speed of Auto programs	